

2 in 1 : Booster and 12 V power supply.

In a single booster, the GYSPACK HERITAGE combines, the starting of classic vehicles equipped with a 6 V battery and modern vehicles equipped with a 12 V battery. It also supplies all types of vehicle with 12 V DC thanks to its two internal 20 Ah batteries.

IDEAL FOR CLASSIC VEHICLES

The GYSPACK HERITAGE's two 6 V batteries enable it to start instantly a wide range of vehicles:

- **classic vehicles (motorbikes and cars)** equipped with 6 V batteries (starting current: 400 A and 3200 A peak). The use of the two batteries (20 Ah) in parallel gives the GYSPACK an energy reserve of 40 Ah.
- **modern vehicles** equipped with 12 V battery (starting current: 450 A and 1600 A in peak).

6 V		12 V				

ELECTRICAL POWER SUPPLY 12 V DC

The 2 integrated 20 Ah batteries are also a **12 V power source** to supply all electrical appliances, television, lamp, laptop, electric cooler...

	4 W 40 h		15 W 13 h		
	9 W 22 h		24 W 8 h		80 W 2,5 h

SERVICE LIGHTING



The GYSPACK HERITAGE is equipped with a lamp consisting of 7 high-brightness LEDs for working in the dark and in hazardous areas.



Supplied with:



12V charger
ref. 054684

PROFESSIONAL EQUIPMENT

- ✓ **Automatic charger 230V / 12 V Floating** : automatic charge of the internal batteries without supervision.
 - Designed to recharge batteries up to 100% for increased life cycle and performance.
 - Safe to be left connected to the mains permanently (charge is recommended after each use).
- ✓ **Built-in tester** to visualise the state of charge of the internal batteries.
- ✓ **ON/OFF battery breaker** protection against overvoltage when charger is connected to the mains.
- ✓ **Sound alarm** to alert the user in case of **polarity reversal**.
- ✓ **Copper cables 2 x 1.80 m, ø25 mm² with 600 A insulated clamps 600 A.**
- ✓ **Equipped with a 300 A front fuse** (supplied with a replacement fuse).

INSIDE	START				TEST		PROTECTION		POWER SUPPLY			
	Battery	I 1V/C	Cranking CC	Peak Battery								
2 x 20 Ah	6 V	400 A	800 A	3200 A	-	EXTERNAL 12V DC / 2 A DC	•	•	12 V DC	300 A	37 x 20 x 46	18
	12 V	450 A	850 A	1600 A								