



Tradicionalni punjač i tester za 12V olovne baterije.

PUNJAČ BATERIJA

- Za sve olovno-kiselinske pojačane baterije od 10 do 45 Ah.
- Indikator napunjenosti.
- Bakreni namot.
- Zaštićen od kratkog spoja i preopterećenja.

ISPITIVAČ

- Voltmetar do 15V.











Skladištenje kabela.

OPĆA ZAŠTITA



- Toplinska zaštita transformatora.
- Zaštićen od promjene polariteta zahvaljujući osiguraču od 10 A.
- Izolirane stezaljke.

CE - EN 60335-2-29

 50-60hz			MIN.  MAX. Ah	 Reg	Efficace/RMS	Moyen/Average (EN 60335)	 fuse	IP	 cm	 kg
230V	70W	12V	10-45Ah	-	4.5A	3A	10A	20	11.5x16x22	2.2

Made in China

www.gys.fr